

WHAT IS CLAIMED IS:

1. A method of providing an automatic loudness compensation circuit comprising:
 - receiving an input audio signal containing bass content;
 - coupling the input audio signal to a voltage detector having an output voltage;
 - 5 coupling the output voltage of the voltage detector to a filter circuit for adjusting a corner frequency associated with the filter circuit such that the corner frequency is inversely related to the input audio signal for boosting the bass content of the input audio signal; and
 - coupling an output of the filter circuit to a power amplifier for amplifying the
 - 10 filter circuit output.
2. The method of claim 1 wherein the method further comprises driving an audio speaker with the amplified filter circuit output.
3. The method of claim 1 wherein the filter circuit further comprises a capacitance multiplier circuit comprising a light emitting device coupled to a light sensitive resistor.
4. The method of claim 3 wherein the capacitance multiplier circuit further comprises a low pass filter coupled to the light emitting device and the light sensitive resistor.
5. The method of claim 4 wherein the filter circuit adjusts the corner frequency of the low pass filter within an operating frequency range.
6. The method of claim 5 wherein the filter circuit adjusts the corner frequency of the low pass filter such that the corner frequency is increased when the input audio signal decreases.

008060-01085960

7. The method of claim 3 wherein the amount boost to the bass content of the input audio signal is proportional to the corner frequency of the low pass filter.

8. The method of claim 3 wherein the amount boost to the bass content of the input audio signal is proportional to the value of the light sensitive resistor.

9. The method of claim 1 wherein the source of the input audio signal is a compact disc.

10. The method of claim 1 wherein the source of the input audio signal is a cassette.

11. The method of claim 1 wherein the source of the input audio signal is a digital video disc.

12. The method of claim 1 wherein the source of the input audio signal is a microphone.

13. The method of claim 12 wherein the output of the filter circuit and the microphone input audio signal are coupled to a summing circuit having an output signal.

14. The method of claim 13 wherein the output of the summing circuit is coupled to the power amplifier.

15. A method of providing an automatic loudness compensation circuit comprising:

receiving an input audio signal including bass content;

coupling the input audio signal to a voltage detector to produce an output voltage;

5 coupling the output voltage of the voltage detector to a control circuit, the control circuit comprising a filter circuit;

comparing a corner frequency associated with the filter circuit to the strength of the input audio signal;

shifting the corner frequency such that the corner frequency is inversely related to the strength of the input audio signal;

coupling an output of the filter circuit to a power amplifier for amplifying the filter circuit output; and

driving an audio speaker with the amplified filter circuit output.

16. The method of claim 15, further comprising:

utilizing a capacitance multiplier circuit comprising a light emitting device coupled to a light sensitive resistor having an output signal wherein the output of the light sensitive resistor is coupled to a low pass filter for adjusting the bass content of the input audio signal.

17. The method of claim 16, further comprising:

responding to an increase in the input audio signal by energizing the light emitting device within the filter circuit to produce a light source; and

decreasing the resistance of the light sensitive resistor; and

increasing the value of the capacitor in order to shift the corner frequency such that bass boosting of the audio input signal is quickly removed.

18. The method of claim 16 further comprising:

responding to a decrease in the audio input signal by de-energizing the light emitting device within the filter circuit in order to prevent a light source;

increasing the resistance of the light sensitive resistor; and

decreasing the value of the capacitor in order to shift the corner frequency such that bass boosting of the audio input signal is slowly added.

19. The method of claim 15 wherein the amount boost to the bass content of the input audio signal is proportional to the corner frequency of the filter circuit.

20. The method of claim 16 wherein the amount boost to the bass content of the input audio signal is proportional to the value of the light sensitive resistor.

21. The method of claim 16, wherein the light sensitive resistor is an opto-coupled resistor.

22. An automatic loudness compensation circuit including a terminal coupled to an input audio signal from an external source and a signal supply having voltage sufficient to drive an output audio speaker comprising:

an R.M.S. detector for providing an R.M.S. voltage from the input audio signal;

5 a control circuit including a filter circuit for adjusting a corner frequency associated with the filter circuit such that the corner frequency is inversely related to the input audio signal;

a power amplifier for increasing the power of the output signal from the low pass filter circuit; and

10 a terminal for providing an amplified output signal.

23. The automatic loudness compensation circuit of claim 22 wherein the control circuit provides a boost to the input audio signal containing a bass content such that the boost is proportional to the corner frequency of the filter circuit.

24. The automatic loudness compensation circuit of claim 22 wherein the filter circuit further comprises a light emitting device coupled to a light sensitive resistor having an output signal wherein the output of the light sensitive resistor is coupled to a low pass filter.

25. The automatic loudness compensation circuit of claim 24 wherein the control circuit provides a boost to the input audio signal containing a bass content such that the boost is proportional to the output of the light sensitive resistor.

means for detecting an R.M.S. voltage from the audio input signal;

means for amplifying the output signal from the filter circuit; and

27. A system for obtaining a first order bass boost compensation comprising:

a terminal for receiving an audio input signal having a signal level;

a level control for determining the level of the input audio signal;

an automatic loudness compensation circuit having an output signal comprising:

an R.M.S. detector coupled to the power supply voltage for providing an

R.M.S. voltage from the input audio signal; and

a summing circuit having an output signal coupled to the automatic loudness compensation circuit for receiving input from a microphone and summing the microphone input to the output of the automatic loudness compensation circuit;

a terminal for providing an amplified output signal to an audio speaker.

28. The method of claim 27, wherein the audio input signal is received from a compact disc player.

29. The method of claim 27, wherein the audio input signal is received from a cassette player.

30. The method of claim 27, wherein the audio input signal is received from a digital video disc player.

31. A system for obtaining an automatic loudness compensation comprising:
an input terminal for receiving an audio input signal having a signal level;
a level control coupled to the input terminal for determining the level of the input audio signal;

5 an automatic loudness compensation circuit having an output signal coupled to the level control comprising a filter circuit for adjusting a corner frequency associated with the filter circuit such that the corner frequency is inversely related to the audio input signal;

10 a summing circuit having an output signal coupled to the automatic loudness compensation circuit for receiving input from a microphone and summing the microphone input to the output of the automatic loudness compensation circuit;

a power amplifier coupled to the summing circuit for increasing the power of the output signal from the summing circuit; and

15 an output terminal coupled to for providing an amplified output signal to an audio speaker.

32. A method for providing an automatic loudness compensation, comprising the steps of:

encoding input variables

processing said encoded input variables; and,

5 decoding said processed encoded input variables into output variables.

33. The method of claim 32, wherein the encoding of said input variables is done by fuzzy sets.

34. The method of claim 32, wherein the processing of the encoded input variables is done by an expert.

35. The method of claim 34, wherein the expert is a rulebase.

36. The method of claim 32, wherein the said decoding of the processed encoded input variables is done by defuzzification.

008060" 0T085960